

RMK QNP Function Table - Keypress Combinations

| Keys Used | PAR (press and release) | PAH (press and hold) |
|------------|---------------------------------|---|
| Mem switch | Toggle the R-M offset frequency | Beacon menu: BE and BA |
| Mem + dit | Send speed | Paddle set of speed, pot options, main menu |
| Mem + dah | Send memory 2 | Record memory 2: M? |
| Mem + both | Send memory 1 | Record memory 1: T? |

RMK QNP Menus

| CW | Menu Item | Pressing a dit | Pressing a dah |
|--|---------------------------|---|--|
| Memory + Dit Menu (PAR mem to advance to the next menu) | | | |
| S | Speed set from paddle | Increase speed 1 wpm | Decrease speed 1 wpm |
| B | Bug / straight key mode | Enables bug mode (dah = key) | Disables bug mode (default) |
| A | Iambic mode A or B | Enables iambic mode A | Enables mode B (default) |
| R | Reverse paddle mode | Reverse dit and dah switches | Reverse did and dah switches |
| AU | Autospace on / off | turns on character autospace | turns off autospace (default) |
| Memory + Dah Menu (PAR mem to exit) | | | |
| M? | Record memory 2 | Records a dit | Records a dah |
| Memory Switch Menu (PAR mem to advance to next menu) | | | |
| BE | Beacon mode - sends mem 1 | Starts the beacon going | Exits the menu |
| Q | Qrss slow speed beacon | turns on slow speed beaconing | turns off slow speed beaconing (default) |
| BA | Beacon alternate mode | Selects alternate beacon sends of mem 1 and mem 2 | Selects send of mem 1 only (default) |
| Memory + Both Menu (PAR mem to exit) | | | |
| T? | Record memory 1 | Records a dit | Records a dah |

Compatibility mode: PAH either dit or dah paddle during powerup to enter the compatibility mode with the original R-M keyer chip. The paddle opposite the one pressed at powerup will act as the straight key.

Add spaces in text strings using the space character di dah dah dah dit. The spaces are not transmitted. Useful for delays in beacon messages etc.